



ARLP-UL-M-KIT

- PTS "PUSH TO SET" TECHNOLOGY
- COMMAND ACCESS DESIGNED CUSTOM MOTOR -- NO CLEARANCE ISSUES
- Full push pad retraction -- Ball screw INTEGRATION FOR INCREASED TORQUE
- Works on all 8000 series
- PATENT PENDING

The new ARLP-UL-M-KIT is a robust, ground breaking field installable motorized latch retraction kit for Adams Rite 8000 series exit devices. It utilizes a custom ball screw assembly and CAT designed custom stepper motor to maximize the pulling force in a package small enough to fit inside all Adams Rite 8000 devices with no clearance issues.. The only hole you'll need to drill is the raceway! It utilizes our PTS "Push to Set" technology making post installation adjustments incredibly easy. Watch the video! You're gonna love it!

SPECIFICATIONS

VOLTAGE:

- Voltage range 22 to 28 VDC
- System protection unit shutdown when voltage exceeds 28VDC
- Average Current Peak 1.3A
- Average Current Hold -170mA
- PTS adjustment approx. 1/4"

WIRE RUN:

- 500' with 18ga wire
- 700' with 16ga wire

PRODUCT DETAILS:

- Box: 10.5" x 3.75": x 2.5"
- Weight: 2 Lbs
- Master Pack Qty: 15 ea.

RECOMMENDED LOCKING HARDWARE POWER SUPPLIES:

- PS204/PS204B
- PS480B

PS210

- PS1
- PS220/220B
- PS2

PS440B

- - - PS5-8

FEATURES:

- MM4 Smart Module: On board diagnostics with audible feedback for adjustment and power issues
- "PTS": 5 second electronic adjustment for easy post installation adjustment
- Electric dogging rated for continuous duty Auto engage if dogged push pad is pulled from position
- Low current draw
- Field switchable to a "High Torque" mode
- Up to 500' wire run with 2-18ga wire Long wire runs provides installer with convenience of placing the locking device power supply in a centralized location; i.e. the same closet as the access panel
- 8' cable with Quick Connect for MM4 module to easily connect to power supply lead
- 3-year "no hassle" warranty

Accessories:

Request to Exit (REX) - Available as a field installable kit

U.S. Customer Support 1-888-622-2377

Visit our website for more details www.CommandAccess.com

Canada Customer Support 1-855-823-3002



How to Order

Part #	Easy Order #	Description				
ARLP-UL-M-KIT	76736	Kit for the Adams Rite 8000 series. EU 24 VDC.				
ARREXKIT-M-ED	79013	Field installable REX kit for Adams Rite 8000 series.				

ARLP-UL-M-KIT MATRIX

The ARLP-UL-M-KIT will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.

		inical incal	Solo Odifica AZA	Modified Ap Soi	46 M	50° (3E)	, o ,
Adams Rite Kit	7 3	Solificon S	35 8	AP S	APA		
ARLP-UL-M-KIT	8000	√	√	√	-	√	
ARREXKIT-M-ED	√	_	1	√	√	√	